
GSM Scout LTE IP65/GPS

Simply supervising with your mobile, SMS event messaging as well as GPS positioning - immediately informed, immediately reaction!



Applications

Supervising of:

- Sailing vessel, boats and yachts
- Camper and Caravans
- Homes

GPS positioning:

- Setting of berthing place by pressing a button
- Automatical messaging by SMS on leaving the berth place
- Request of the latest GPS position by SMS

Telemetry of electrical devices:

- Bilge pump
- Light
- Cooler

General informations

The GSM Scout LTE IP65/GPS is an inexpensive and easy solution for the supervision of movable objects like boats, yachts, caravans or campers as well as the supervising of homes. Over connected sensors the device grasps, e.g., burglaries, upcoming fire, water or other serious events. These are immediately sent by SMS to any mobile phone and the user is able to initiate immediately countermeasures. The system is simply configurable about the phone number memory of the SIM-card and is ready for use immediately. Further it is possible to activate the relais outputs by an SMS. So the user is able to switch different devices on board on or off. GPS is it possible to localiye the position of the GSM Scout LTE and the supervised object. The position will be sended as an SMS.

For protecting the circuities of burning damages, using a R/C protection combination is recommended.

Physical Dimensions / 100 x 90 x 25 mm (L x H x W) / 140 g

2 relais contacts

11 - 35 V DC , 90 mA

900 & 1800 Mhz or 850 & 1900 Mhz r

Programming of the SIM-card over the r

- 30 °C bis + 60 °C work temperatur

registration circle for "burglary"
registration circle for "fire"
registration circle for "water"
registration circle for "arbitrary event"

Technical data

GSM networks Configuration

Temperature range

weight

Interfaces

Energy supply

Technical specific features

- Comfortable connection about screw contacts
- The easy configuration about SIM-card, without software
- Small dimensions, splashwaterproof (lp65)
- Incl. Lithium polymer battery

DIESES PROJEKT WIRD VOM

EUROPÄISCHEN FONDS FÜR REGIONALE

- 2 relais contacts for switching devices
- Customizable event messages
- GPS positioning via SMS

Functional extension e-mail

Alarm text via e-mail (in addition to SMS)

Conditions

To use the GSM Scout LTE IP65/GPS, you need: Power supply, activated SIM-card (prepaid or fix contract), Sensors

networks mobile phone	Scope of supply	GSM Scout LTE IP65/GPS Manual Miniatur screw driver	
	Functional extension	Alarm message and arming via e-mail and/or SMS, Configuration with USB cable on the PC, server setup and usage for 1 year Order no. 701100921 (used for 1 year)	
	Optionale accessories	Main power supply 12 V DC Glass attached antenna (indoor use), 2.5 m cable (SMA) LTE antenna omnidirectional (outdoor use), 2.5 m cable (SMA) R/C protection Various sensors on request	Order no. 305307214 300303304\$ 30030331050 700100618

ConiuGo Gesellschaft für Telekommunikation mbH Berliner Straße 4a 16540 Hohen Neuendorf





06/2014