


# GSM Scout Professional LTE



Monitoring, remote control and optional position tracking  
by SMS from your cell phone - direct informed, direct reaction

Order no.: 700100214L


## Applications

Monitoring of:

- Heatings, reefers and server rooms
- Buildings and objects
- Plants and machines
- Boats, yachts, campers and caravans
- Home

Remote switching of:

- Bilge pump
- Light
- Air conditioner



## General information

The GSM Scout Professional LTE is a professional solution for monitoring objects. The device detects e.g. Burglary, upcoming fire, entrance of water, or other fundamental incidents, with its connected sensors. Those are sent immediately by SMS to a choosable cell phone, which allows direct reaction. The system is easy to customize with the dial number storage of the SIM card and instant ready to use. Furthermore it is possible to activate the relais output by SMS. That makes switching on or off possible, for a huge number of devices. An optional extension is the tracking by SMS. The GSM Scout Professional LTE is able to detect its position and sending an SMS, in the case of unauthorized movements.

For protecting the circuitries of burning damages, using a R/C protection combination is recommended.

## Technical features

- Easy installation with screws, programming by SMS
- Easy setting bei SIM card, without software
- Transmitting of credits for prepaid SIM card
- Transmitting of the signal quality
- Different alarm texts possible, internal lithium polymer battery
- Position tracking by SMS, geofencing (optional)

## Functional extension e-mail

Alarm text via e-mail (in addition to SMS)

## Conditions

For using the GSM Scout Professional LTE is required:  
SIM card (prepaid or contract), sensors

## Technical data

<b>Mobile network</b>	Usable with all european mobile providers, others on request
<b>Customization</b>	SIM card programming by cell phone
<b>Dimensions / weight</b>	110 x 100 x 75 mm (W x L x H) / 219 g
<b>Temperature range</b>	- 30 °C up to + 60 °C working temperature
<b>Interfaces</b>	1 circuit for "burglary" 1 circuit for "fire" 1 circuit for "water" 1 circuit for "configurable incident" 2 x relais switching contacts NO
<b>Power supply</b>	11 - 35 V DC , 90 mA - 130 mA, internal lithium polymer battery

<b>Scope of delivery</b>	GSM Scout Professional LTE Manual Miniature screw driver Screws for housing mounting
<b>Functional extension</b>	Alarm message and arming via e-mail and/or SMS, Configuration with USB cable on the PC, server setup and usage for 1 year <b>Order no.</b> 701100921 (used for 1 year)
<b>Optional accessoires</b>	Power supply 230 V AC / 12 V D Glass attached antenna (indoor), 1.5 m cable (SMA) Round antenna PUK (outdoor), 3 m cable (SMA) GPS receiver (external applications) R/C protection
<b>Order no.</b>	305307214 300303304S 300303310S 700100618