


GSM Scout active LTE



Simply supervising with your mobile and SMS - immediately informed, immediately reaction! Connect, adjusting, ready!

Order no.: 700100209L


Applications

Supervising of:

- Sailing vessel, boats and yachts
- Camper and Caravans
- Homes

Telemetry of electrical devices:

- Bilge pump
- Light
- Cooler



General informations

The GSM Scout active LTE is an inexpensive and easy solution for the supervision of movable objects like boats, yachts, caravans or campers as well as the supervising of homes. Over connected sensors the device grasps, e.g., burglaries, upcoming fire, water or other serious events. These are immediately sent by SMS to any mobile phone and the user is able to initiate immediately countermeasures. The system is simply configurable about the phone number memory of the SIM-card and is ready for use immediately.

Further it is possible to activate the relais outputs by an SMS. So the user is able to switch different devices on board on or off.

For protecting the circuitries of burning damages, using a R/C protection combination is recommended.

Technical specific features

- Comfortable connection about screw contacts
- The easy configuration about SIM-card, without software
- Small construction style
- 2 relais contacts for switching devices
- Customizable event messages

Functional extension e-mail

Alarm text via email (in addition to SMS)

Conditions

To use the GSM Scout active LTE, you need:

Power supply, activated SIM-card (prepaid or fix contract), Sensors

Technical data

GSM networks	900 & 1800 Mhz or 850 & 1900 Mhz networks
Configuration	Programming of the SIM-card over the mobile phone
Physical Dimensions / weight	100 x 90 x 25 mm (L x H x W) / 140 g
Temperature range	- 30 °C bis + 60 °C work temperature
Interfaces	1 registration circle for "burglary" 1 registration circle for "fire" 1 registration circle for "water" 1 registration circle for "arbitrary event"
Energy supply	11 - 35 V DC , 60 mA

Scope of supply	GSM Scout active LTE Manual Miniatur screw driver
Funktional extension	Alarm message and arming via email and/or SMS, configuration with USB cable on the PC, server setup and usage for 1 year Order no. 701100921 (used for 1 year)
Optionale accessories	Mains Power Supply 12 V DC Glass Attached Antenna (Indoor use), 1,5 m cable (SMA) Round Antenna PUK (Outdoor use), 3 m cable (SMA) R/C protection Various sensors on request
Order no.	305307214 3003033045 3003033105 700100618